

## 12V DC to AC 100 Watt Power Inverter



### DIRECT PLUG-IN

This ultra slim pocket size inverter plugs into your cigarette lighter or to airplane DC socket to power laptops, cell phone chargers and other small electronic devices

This unit has the following features:

- 100 watts continuous power
- 200 watts peak power
- Provides 0.9 Amps
- Carbon Fiber Design
- 120 volt AC outlet
- Overload Indicator
- USB Output Port
- Direct Cigarette lighter Connection
- CE Approved and RoHS Compliant

**CARBON  
FIBER  
DESIGN**

**MICRO  
CHIP  
TECHNOLOGY**

**USB  
CONNECTION**

Output Wave Form	Modified Sinewave
No-load draw	< 0.1 amp
Efficiency	Up to 90%
Input voltage range	10-15.5 VDC
Over voltage shutdown	over 15.5 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible at 10.6 VDC
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	One 3-Prong
Warranty	2 year
Inverter weight	0.25 lbs
Dimensions (W x H x D)	5.8 x 1.5 x 2.8 in.